Product data sheet

LEXI LED - 1W - 4000K - STANDARD EMERGENCY - EURO DOWN ARROW ELX17461

THORLUX LIGHTING








LED emergency exit signs with downlighter LED array which illuminates the exit doorway. Ceiling, wall, cantilever or suspension fixing. Fast-change battery replacement reduces maintenance time and cost. Applications: commercial environments, schools, hospitals, banks, libraries etc EURO Down Arrow

Light output 1 (integrated, emergency)



Lamp type	LED	CCT	4000 K
Nominal lamp power	1.7 W	CRI	80
Total flux	110 lm	LOR	100%
Luminous efficacy	65 lm/W	ULOR	26%
		Total nower	1 7 W

Mounting mode

Wall mounted, Pendant

Shape and measurements

Length: 11.81 in Width: 7.24 in Height: 1.46 in

Adjustability

Fixed, Height adjustable

Electric

System power: 1.7 W

Information regarding emergency functions

Emergency lighting only Emergency sign: N/A

Protection

IP: 40