# Product data sheet

LUMINAIRE REVARA L1400 SINGLE 11,1-25,7W 3000K 10.09703.2VXXX

HESS








Luminaire with style-defining design ribs made of cast aluminum. Glass cover of ESG float glass. Inclination of the luminaire adjustable from 0° - 30° in 5° steps. Cable protection hose made of weatherproof plastic mesh. Bracket made of steel, galvanized, painted in housing color.

REVARA L1400: Opening and exchange of glass without tools. Exchange of LED boards and driver possible without any tools - and separately.

Spigot with diameter 76.1 mm. Overhanging: 1420 mm. 1 bracket REVARA L1400 single Made of galvanised steel Spigot ø 76,1 mm Overhang from centre of spigot to outer edge of luminaire 1430 mm pre-wired (8000 mm)

#### Light output 1



1 x LED		
Nominal lamp power	11.1 W	LOR
Lamp flux	1420 lm	Total flux
Luminous efficacy	128 lm/W	Total power
CCT	3000 K	
CRI	80	



1 x LED			
Nominal lamp power	13.5 W	LOR	100%
Lamp flux	1494 lm	Total flux	1494 lm
Luminous efficacy	111 lm/W	Total power	13.5 W
CCT	3000 K		
CRI	80		



1 x LED			
Nominal lamp power	13.5 W	LOR	100%
Lamp flux	1585 lm	Total flux	1585 lm
Luminous efficacy	117 lm/W	Total power	13.5 W
CCT	3000 K		
CRI	80		

100% 1420 lm 11.1 W

|--|

Nominal lamp power	13.5 W	LOR	100%
Lamp flux	1745 lm	Total flux	1745 lm
Luminous efficacy	129 lm/W	Total power	13.5 W
CCT	3000 K		
CRI	80		



#### 1 x LED

I X LLD			
Nominal lamp power	16 W	LOR	100%
Lamp flux	2046 lm	Total flux	2046 lm
Luminous efficacy	128 lm/W	Total power	16 W
CCT	3000 K		
CRI	80		




# 1 x LED

Nominal lamp power	16 W	LOR	100%
Lamp flux	2066 lm	Total flux	2066 lm
Luminous efficacy	129 lm/W	Total power	16 W
CCT	3000 K		
CRI	80		



# 1 x LED


I X LLD			
Nominal lamp power	18.3 W	LOR	100%
Lamp flux	2108 lm	Total flux	2108 lm
Luminous efficacy	115 lm/W	Total power	18.3 W
CCT	3000 K		
CRI	80		



Nominal lamp power	16 W	LOR	100%
Lamp flux	1765 lm	Total flux	1765 lm
Luminous efficacy	110 lm/W	Total power	16 W
CCT	3000 K		
CRI	80		



Nominal lamp power	23 W	LOR	100%
Lamp flux	2948 lm	Total flux	2948 lm
Luminous efficacy	128 lm/W	Total power	23 W
CCT	3000 K		
CRI	80		



#### 1 x LED

IXLLD			
Nominal lamp power	16 W	LOR	100%
Lamp flux	1740 lm	Total flux	1740 lm
Luminous efficacy	109 lm/W	Total power	16 W
CCT	3000 K		
CRI	80		



# 1 x LED

Nominal lamp power	16 W	LOR	100%
Lamp flux	1847 lm	Total flux	1847 lm
Luminous efficacy	115 lm/W	Total power	16 W
CCT	3000 K		
CRI	80		



# 1 x LED

Nominal lamp power	16 W	LOR	100%
Lamp flux	2033 lm	Total flux	2033 lm
Luminous efficacy	127 lm/W	Total power	16 W
CCT	3000 K		
CRI	80		



Nominal lamp power	18.3 W	LOR	100%
Lamp flux	2448 lm	Total flux	2448 lm
Luminous efficacy	134 lm/W	Total power	18.3 W
CCT	3000 K		
CRI	80		


|--|

Nominal lamp power	13.5 W	LOR	100%
Lamp flux	1576 lm	Total flux	1576 lm
Luminous efficacy	117 lm/W	Total power	13.5 W
CCT	3000 K		
CRI	80		



#### 1 x LED

I X LLD			
Nominal lamp power	18.3 W	LOR	100%
Lamp flux	2357 lm	Total flux	2357 lm
Luminous efficacy	129 lm/W	Total power	18.3 W
CCT	3000 K		
CRI	80		




# 1 x LED

Nominal lamp power	18.3 W	LOR	100%
Lamp flux	2111 lm	Total flux	2111 lm
Luminous efficacy	115 lm/W	Total power	18.3 W
CCT	3000 K		
CRI	80		
CRI	80		



# 1 x LED

Nominal lamp power	16 W	LOR	100%
Lamp flux	1914 lm	Total flux	1914 lm
Luminous efficacy	120 lm/W	Total power	16 W
CCT	3000 K		
CRI	80		



Nominal lamp power	23 W	LOR	100%
Lamp flux	2524 lm	Total flux	2524 lm
Luminous efficacy	110 lm/W	Total power	23 W
CCT	3000 K		
CRI	80		

|--|

Nominal lamp power	13.5 W	LOR	100%
Lamp flux	1642 lm	Total flux	1642 lm
Luminous efficacy	122 lm/W	Total power	13.5 W
CCT	3000 K		
CRI	80		



#### 1 x LED

I X LLD			
Nominal lamp power	25.7 W	LOR	100%
Lamp flux	2921 lm	Total flux	2921 lm
Luminous efficacy	114 lm/W	Total power	25.7 W
CCT	3000 K		
CRI	80		




# 1 x LED

Nominal lamp power	25.7 W	LOR	100%
Lamp flux	3254 lm	Total flux	3254 lm
Luminous efficacy	127 lm/W	Total power	25.7 W
CCT	3000 K		
CRI	80		




# 1 x LED

Nominal lamp power	25.7 W	LOR	100%
Lamp flux	3286 lm	Total flux	3286 lm
Luminous efficacy	128 lm/W	Total power	25.7 W
CCT	3000 K		
CRI	80		



Nominal lamp power	25.7 W	LOR	100%
Lamp flux	3044 lm	Total flux	3044 lm
Luminous efficacy	118 lm/W	Total power	25.7 W
CCT	3000 K		
CRI	80		

Nominal lamp power	25.7 W	LOR	100%
Lamp flux	2807 lm	Total flux	2807 lm
Luminous efficacy	109 lm/W	Total power	25.7 W
CCT	3000 K		
CRI	80		




#### 1 x LED

IXLLD			
Nominal lamp power	25.7 W	LOR	100%
Lamp flux	2770 lm	Total flux	2770 lm
Luminous efficacy	108 lm/W	Total power	25.7 W
CCT	3000 K		
CRI	80		




# 1 x LED

Nominal lamp power	25.7 W	LOR	100%
Lamp flux	2938 lm	Total flux	2938 lm
Luminous efficacy	114 lm/W	Total power	25.7 W
CCT	3000 K		
CRI	80		



# 1 x LED

====			
Nominal lamp power	25.7 W	LOR	100%
Lamp flux	3234 lm	Total flux	3234 lm
Luminous efficacy	126 lm/W	Total power	25.7 W
CCT	3000 K		
CRI	80		



Nominal lamp power	18.3 W	LOR	100%
Lamp flux	2288 lm	Total flux	2288 lm
Luminous efficacy	125 lm/W	Total power	18.3 W
CCT	3000 K		
CRI	80		

|--|

Nominal lamp power	23 W	LOR	100%
Lamp flux	2678 lm	Total flux	2678 lm
Luminous efficacy	116 lm/W	Total power	23 W
CCT	3000 K		
CRI	80		



#### 1 x LED

TALLD			
Nominal lamp power	16 W	LOR	100%
Lamp flux	1837 lm	Total flux	1837 lm
Luminous efficacy	115 lm/W	Total power	16 W
CCT	3000 K		
CRI	80		



# 1 x LED

Nominal lamp power	23 W	LOR	100%
Lamp flux	2663 lm	Total flux	2663 lm
Luminous efficacy	116 lm/W	Total power	23 W
CCT	3000 K		
CRI	80		



# 1 x LED

I X LLD			
Nominal lamp power	11.1 W	LOR	100%
Lamp flux	1406 lm	Total flux	1406 lm
Luminous efficacy	127 lm/W	Total power	11.1 W
CCT	3000 K		
CRI	80		



====			
Nominal lamp power	11.1 W	LOR	100%
Lamp flux	1316 lm	Total flux	1316 lm
Luminous efficacy	119 lm/W	Total power	11.1 W
CCT	3000 K		
CRI	80		

1	Χ	L	E	D

Nominal lamp power	11.1 W	LOR	100%
Lamp flux	1213 lm	Total flux	1213 lm
Luminous efficacy	109 lm/W	Total power	11.1 W
CCT	3000 K		
CRI	80		




I X LED			
Nominal lamp power	11.1 W	LOR	100%
Lamp flux	1263 lm	Total flux	1263 lm
Luminous efficacy	114 lm/W	Total power	11.1 W
CCT	3000 K		
CRI	80		



# 1 x LED

Nominal lamp power	11.1 W	LOR	100%
Lamp flux	1197 lm	Total flux	1197 lm
Luminous efficacy	108 lm/W	Total power	11.1 W
CCT	3000 K		
CRI	80		



# 1 x LED

Nominal lamp power	11.1 W	LOR	100%
Lamp flux	1270 lm	Total flux	1270 lm
Luminous efficacy	114 lm/W	Total power	11.1 W
CCT	3000 K		
CRI	80		



Nominal lamp power	11.1 W	LOR	100%
Lamp flux	1398 lm	Total flux	1398 lm
Luminous efficacy	126 lm/W	Total power	11.1 W
CCT	3000 K		
CRI	80		

|--|

Nominal lamp power	13.5 W	LOR	100%
Lamp flux	1756 lm	Total flux	1756 lm
Luminous efficacy	130 lm/W	Total power	13.5 W
CCT	3000 K		
CRI	80		




#### 1 x LED

I X LLD			
Nominal lamp power	13.5 W	LOR	100%
Lamp flux	1514 lm	Total flux	1514 lm
Luminous efficacy	112 lm/W	Total power	13.5 W
CCT	3000 K		
CRI	80		



# 1 x LED

Nominal lamp power	13.5 W	LOR	100%
Lamp flux	1773 lm	Total flux	1773 lm
Luminous efficacy	131 lm/W	Total power	13.5 W
CCT	3000 K		
CRI	80		



# 1 x LED


Nominal lamp power	20.7 W	LOR	100%
Lamp flux	2386 lm	Total flux	2386 lm
Luminous efficacy	115 lm/W	Total power	20.7 W
CCT	3000 K		
CRI	80		



Nominal lamp power	18.3 W	LOR	100%
Lamp flux	2320 lm	Total flux	2320 lm
Luminous efficacy	127 lm/W	Total power	18.3 W
CCT	3000 K		
CRI	80		

|--|

Nominal lamp power	20.7 W	LOR	100%
Lamp flux	2372 lm	Total flux	2372 lm
Luminous efficacy	115 lm/W	Total power	20.7 W
CCT	3000 K		
CRI	80		




#### 1 x LED

I X LLD			
Nominal lamp power	20.7 W	LOR	100%
Lamp flux	2644 lm	Total flux	2644 lm
Luminous efficacy	128 lm/W	Total power	20.7 W
CCT	3000 K		
CRI	80		



# 1 x LED

Nominal lamp power	20.7 W	LOR	100%
Lamp flux	2472 lm	Total flux	2472 lm
Luminous efficacy	119 lm/W	Total power	20.7 W
CCT	3000 K		
CRI	80		



# 1 x LED

Nominal lamp power	20.7 W	LOR	100%
Lamp flux	2280 lm	Total flux	2280 lm
Luminous efficacy	110 lm/W	Total power	20.7 W
CCT	3000 K		
CRI	80		



Nominal lamp power	20.7 W	LOR	100%
Lamp flux	2642 lm	Total flux	2642 lm
Luminous efficacy	128 lm/W	Total power	20.7 W
CCT	3000 K		
CRI	80		

|--|

Nominal lamp power	18.3 W	LOR	100%
Lamp flux	1986 lm	Total flux	1986 lm
Luminous efficacy	109 lm/W	Total power	18.3 W
CCT	3000 K		
CRI	80		



#### 1 x LED

IXLED			
Nominal lamp power	20.7 W	LOR	100%
Lamp flux	2249 lm	Total flux	2249 lm
Luminous efficacy	109 lm/W	Total power	20.7 W
CCT	3000 K		
CRI	80		




# 1 x LED

Nominal lamp power	18.3 W	LOR	100%
Lamp flux	2198 lm	Total flux	2198 lm
Luminous efficacy	120 lm/W	Total power	18.3 W
CCT	3000 K		
CRI	80		



# 1 x LED

Nominal lamp power	20.7 W	LOR	100%
Lamp flux	2627 lm	Total flux	2627 lm
Luminous efficacy	127 lm/W	Total power	20.7 W
CCT	3000 K		
CRI	80		



Nominal lamp power	23 W	LOR	100%
Lamp flux	2966 lm	Total flux	2966 lm
Luminous efficacy	129 lm/W	Total power	23 W
CCT	3000 K		
CRI	80		



23 W	LOR	100%
2996 lm	Total flux	2996 lm
130 lm/W	Total power	23 W
3000 K		
80		
	2996 lm 130 lm/W 3000 K	2996 lm Total flux 130 lm/W Total power 3000 K



#### 1 x I FD

I X LLD			
Nominal lamp power	23 W	LOR	100%
Lamp flux	2774 lm	Total flux	2774 lm
Luminous efficacy	121 lm/W	Total power	23 W
CCT	3000 K		
CRI	80		



# 1 x LED

Nominal lamp power	23 W	LOR	100%
Lamp flux	2559 lm	Total flux	2559 lm
Luminous efficacy	100 lm/W	Total power	25.7 W
CCT	3000 K		
CRI	80		



# 1 x LED

CRI

Nominal lamp power	20.7 W	LOR	100%
Lamp flux	2669 lm	Total flux	2669 lm
Luminous efficacy	129 lm/W	Total power	20.7 W
CCT	3000 K		

80

# Mounting mode

Pole top mounted, Pole integrated

# Shape and measurements

Length: 43.29 in Width: 14.58 in Height: 10.98 in

# Adjustability

Tiltable

# Electric

System power: 11.1-25.7 W

# Protection

IP: 65