# Product data sheet

MOON SLIM EM 320 EMERGENCY MODULE 7508558

HIDE-A-LITE








Emergency lighting module suitable for Moon Slim. Installed using the accompanying screws. The luminaires can be finished with emergency lighting modules afterwards and will retain their normal capacity and control function. Should be put into use within 6 months to retain function, (spare battery available as an accessory). The emergency lighting module is equipped with automatic self-testing and indicates status via green or red LED. Provides light for 1.5 hours with power failure.

### Light output 1 (emergency)



1 x LED
Nominal lamp power
Lamp flux
Luminous efficacy
CCT
CRI

3.3 W	LOR	100%
234 lm	ULOR	3%
71 lm/W	Total flux	234 lm
4000 K	Total power	3.3 W
80		

#### Mounting mode

Ceiling mounted, Wall mounted

#### Shape and measurements

Height: 2.60 in Diameter: 12.60 in

#### Adjustability

Fixed

#### Electric

System power: 3.3 W Appliance Class: II

## Information regarding emergency functions

Emergency lighting only Emergency sign: N/A

# Protection

IP: 44

Designation labels: CE